### Surface Mount

# **RF Transformer**

0.2 to 350 MHz


Operating Temperature	-20°C to 85°C
Storage Temperature	-55°C to 100°C
RF Power	0.25W
DC Current	30mA
Permanent damage may occur if any o	f these limits are exceeded.

### **Pin Connections**


**Maximum Ratings** 

PRIMARY DOT	4
PRIMARY	6
SECONDARY DOT	3
SECONDARY	1
SECONDARY CT	2
NOT USED	5

### **Outline Drawing**



NOTE: PIN NUMBERS DO NOT APPEAR ON UNIT, FOR REFERENCE ONLY. INDEX MARK NEAR PIN 6.



### Outline Dimensions (inch )

F	Е	D	С	В	Α
.020	.042	.010	.23	.27	.30
0.51	1.07	0.25	5.84	6.86	7.62
wt	L	K	J	Н	G
grams	.036	.31	.09	.05	.100
0.50	0.91	7.87	2.29	1.27	2.54

## Config. A O SEC

### **Features**

- wideband, 0.2 to 350 MHz
- · good return loss
- also available with surface mount gull wing (KK81) plug-in (X65) leads

### **Applications**

- impedance matching
- receivers/transmitters
- balance antennas



CASE STYLE: W38 PRICE: \$3.25 ea. QTY (1-9)

+ RoHS compliant in accordance with EU Directive (2002/95/EC)

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications.

### **Transformer Electrical Specifications**


Ω <b>RATIO</b> (Secondary/Primary)	FREQUENCY (MHz)	INSERTION LOSS*		
		3 dB MHz	2 dB MHz	1 dB MHz
4	0.2-350	0.2-350	0.35-300	2-100

<sup>\*</sup>Insertion Loss is referenced to mid-band loss, 0.6 dB typ.

### **Typical Performance Data**

FREQUENCY (MHz)	INSERTION LOSS (dB)	INPUT R. LOSS (dB)	
0.20	2.06	3.31	
0.35	1.33	7.01	
0.50	1.13	9.36	
1.00	0.92	12.67	
2.00	0.72	15.24	
5.00	0.59	17.34	
100.00	0.73	15.07	
175.10	0.91	12.93	
300.00	1.23	12.36	
350.00	1.34	13.08	





For detailed performance specs

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minicipouits.com